

CZ Uživatelská příručka k napájecím zdrojům pro LED pásy

Gratulujeme Vám k zakoupení napájecího zdroje značky McLED! Aby Vám náš výrobek dlouho a dobře sloužil, přečtěte si, prosím, před jeho instalací pečlivě tento manuál.

Instalaci napájecích zdrojů mohou provádět pouze kvalifikované osoby.

Vlastnosti napájecích zdrojů McLED

- Napájecí zdroj je vybaven integrovanou ochranou proti přetížení i zkratu. K obnově funkce dojde po odstranění příčiny poruchy.
- Nominální výkon zdroje uvádí maximální zátěž, kterou lze ke zdroji krátkodobě připojit.
- Pro maximální životnost napájecího zdroje nezatěžujte zdroj na více než 80 % nominální hodnoty (např. ke zdroji o nom. výkonu 100 W nepřipojujte zátěž více než 80 W).
- Vysoká účinnost – šetření elektrické energie.
- Kompaktní velikost a snadná instalace.
- Napájecí zdroje (IP20) jsou vhodné pro použití v interiérech (suché prostředí).

Instalace a pracovní prostředí


1. Zajistěte, aby se vstupní napětí pohybovalo pouze v rozmezí uvedeném na štítku v technických parametrech zdroje.
2. Ujistěte se, že zdroj bude pracovat v čistém prostředí, a že stupeň krytí zdroje odpovídá zvolenému prostředí.
3. Nepřetěžujte zdroj – doporučené zatížení je pouze 80% jmenovitého výkonu zdroje.
4. Při zapnutém napájecím zdroji neodpojujte v žádném případě zátěž.
5. Vždy zajistěte dobré odvětrávání zdroje, tak jak je uvedeno na obrázku. (A)
6. Zdroje lze instalovat na dřevo nebo normálně hořlavý podklad. Neumísťujte na sebe. (B)
7. Napájecí zdroje neumísťujte do vznětlivých a výbušných prostředí. (C)

Napájecí zdroje se síťovou zástrčkou a konektorem		Napájecí zdroje vybavené svorkovnicí	
výkon	náběhový proud	výkon	náběhový proud
12 W	40A	12 W	40A
24 W	50A	40 W	40A
36 W	65A	60 W	40A
48 W, 60 W	80A	72 W	50A
84 W	100A	100 W	100A
96 W	65A	150 W	65A
120 W	120A	180W, 200W	65A

Připojení napájecích zdrojů

Napájecí zdroje se síťovou zástrčkou a konektorem:

Polarita výstupního konektoru:



Napájecí zdroje vybavené svorkovnicí:

Před instalací vždy odpojte napájení. Ujistěte se, že propojovací kabely jsou správně zapojeny.

INPUT (L, N) = vstupní AC napětí

OUTPUT (+, -) = výstupní DC napětí (12/24 V)

Upozornění pro připojování kabelů a zátěže:

1. Napájecí zdroj bude automaticky chráněn v případě, že zátěž překročí maximální jmenovitý výstupní výkon (o 5 % až 20 % nad hodnotu maximálního výkonu).
2. Uvědomte si, že při dlouhém vedení dochází k úbytkům napětí. Vyhybte se proto dlouhým vedením.
3. Řádně vybírejte průřez propojovacího kabelu vzhledem k úbytkům napětí.

Řešení problémů:

Napájecí zdroje jsou vybavené ochranami, které odpojí zdroj vždy při zkratu nebo přetížení. Abyste předešli potížím, je v každém případě potřeba před prvním zapnutím napájecího zdroje řádně zkontrolovat celé zapojení.

Zapojení nefunguje, nesvítí:

1. Zkontrolujte zapojení a vstupní napájení
2. Zkontrolujte, zda na výstupu nedošlo ke zkratu
3. Zkontrolujte na výstupu správné zapojení + a -.
4. Zkontrolujte, zda na zdroji svítí kontrolka LED, pokud je jí vybaven.

Přehřívání zdroje:

1. Dodržujte správné odvětrávání zdroje
2. Zkontrolujte, zda nedochází k přetěžování zdroje.

Nestabilní výstup (blikání):

1. Zkontrolujte, zda nedochází k přetěžování zdroje, nebo nejsou poškozené výstupní vodiče.
2. Zkontrolujte, zda napájecí zdroj není umístěn v prostředí se silným rušením, nebo silným magnetickým polem.

LED pásek řádně nesvítí, je pohaslý:

1. Zkontrolujte výstupní napětí (12V nebo 24V).
2. Zkontrolujte, zda jsou řádně vybrány vodiče vzhledem k úbytkům napětí.
3. Zkontrolujte, zda není napájecí zdroj přetížen.

Pracovní prostředí

Provozní teplota: 0 °C až +40 °C, relativní vlhkost: 75 %

Skladovací prostředí: -20 °C až +60 °C, relativní vlhkost: 90 %

Významy symbolů:

- Může být instalován na dřevěný materiál (např. nábytek).
- Může být instalován na normálně hořlavý povrch (např. dřevo).
- Může být montován na povrch bez další izolace.
- Bezpečnostní oddělovací transformátor, odolný proti zkratu.
- „Safety Extra - Low Voltage IV (SELV) - zdroj bezpečného malého napětí.
- Až Vám náš produkt doslouží, odevzdejte jej prosím na sběrná místa pro elektroodpad.

GB User manual for power supply for LED strips

Congratulations on buying a McLED power supply! To ensure that your products serves you well and long time, please read this manual carefully prior to installing it.

Power supplies may only installed by qualified persons.

Characteristics of McLED power supplies

- The power supply is fitted with integrated overload and short-circuit protection.
- The nominal output of the power supply specifies the maximum load that can be connected to the supply short-term.
- To achieve the longest possible lifespan of the power supply, keep the power supply load up to 80% of the nominal value (for example, if your power supply has the output of 100 W, do not connected load exceeding 80 W.)
- High efficiency - power saving.
- Compact size and easy installation.
- IP20 power supplies are suitable for use in interiors (dry environments).

Installation and operating environment

1. Ensure that the input voltage is within the specified technical parameters placed on the power supply.
2. Ensure that the power supply operates in a clean environment and that the level of coverage of the power supply is adequate for the relevant environment.
3. Do not overload the power supply - the recommended load is up to 80% of the nominal output of the power supply.
4. Never disconnect the load while the power supply is switched on.
5. Ensure proper ventilation for the power supply as shown in the image. (A)
6. The supplies can be installed on wood or other flammable materials. Do not place supplies on top of each other. (B)
7. Do not place power supplies in flammable or explosive environments. (C)


Power supplies with a network plug and connector		Power supplies fitted with a screw terminal	
power	inrush current	power	inrush current
12 W	40A	12 W	40A
24 W	50A	40 W	40A
36 W	65A	60 W	40A
48 W, 60 W	80A	72 W	50A

Power supplies with a network plug and connector		Power supplies fitted with a screw terminal	
power	inrush current	power	inrush current
84 W	100A	100 W	100A
96 W	65A	150 W	65A
120 W	120A	180W, 200W	65A

Connecting power supplies

Power supplies with a network plug and connector:

Polarity of output connector:



Power supplies fitted with a screw terminal:

Always disconnect from power supply before installation. Ensure that the connecting cables are connected correctly.

INPUT (L, N) = input AC voltage

OUTPUT (+, -) = output DC voltage (12/24 V)

Warning for connecting cables and load:

1. The power supply will be automatically protected if the load exceeds the maximum nominal output performance (5 % to 20 % over the maximum output value).
2. Be aware that long leads result in voltage drop. Therefore, avoid using long leads.
3. Select an interconnecting cable with the appropriate cross section in view of voltage drop.

Troubleshooting:

The power supplies are fitted with protections that disconnect the power supply whenever short circuit or overload occurs. To avoid any problems, it is necessary to check the entire connection carefully before switching the power supply on for the first time.

Connection is not working, lights are not on:

1. Check the connection and the input power.
2. Check that short circuit did not occur on the output.
3. Check the correct connection of + and - on the output.
4. Check if the LED warning light on the power supply is on, if the power supply is fitted with this light.

Power supply is overheating:

1. Observe correct ventilation of the power supply.
2. Check that the power supply is not being overloaded.

Unstable output (flashing):

1. Check that the power supply is not being overloaded and that the output cables are not damaged.
2. Check that the power supply is not placed in an environment with strong interference or strong magnetic field.

LED strip does not light properly, the light is weak:

1. Check the output voltage (12V or 24V).
2. Check that appropriate cables have been selected in view of voltage drop.
3. Check that the power supply is not being overloaded.

Operating environment

Operating temperature: 0 °C až +40 °C, relative humidity: 75 %

Storage conditions: -20 °C až +60 °C, relative humidity: 90 %

