



ARGUS Presence detector DALI 230V - 2 zones master



Version	Art. no.
white	CCT552006

Presence detectors for activating up to 2x 25 DALI ballasts.

Functions:

- Presence detection via passive infra-red technology
- Switching and dimming DALI electronic ballasts
- Constant lighting control
- 2 zones brightness management
- Master/slave function for detection extension
- Can be extended with max. 10 slave detectors
- Input for external switches for manual override
- Optional wireless remote control
- DALI power supply integrated
- Max. 25 DALI ballasts per zone

Mains voltage: AC 220-240 V, 50/60 Hz

Output 1

- Max. 25 DALI ballasts

Output 2

- Max. 25 DALI ballasts

Power consumption: < 0.5 W

Angle of detection: 360°

Range: Radius of max. 4 m (at 2.5 m mounting height)

Lux range output 1: 10-2000 Lux

Lux range output 2: 25-100% of Lux range 1

Time setting: from 1 min to 60 min

Standby Time setting: 5, 10, 15 min and ∞

Standby Illumination setting: 10%, 20%, 30% and OFF

Switching mode: Automatic

Connection: 3-wire, neutral conductor **required**

Operating temperature: at room temperature

IP protection rating: IP40 or IP 42 depending on installation type

Colour: white

Dimensions (LxWxH):

Ø102 x 90 mm (flush mounted)

Ø102 x 59 mm (surface mounted)

Accessories: ARGUS Presence detector DALI 230V - slave CCT555006

IR remote control for ARGUS Presence detector DALI 230V CCT556006

IR remote control for ARGUS Presence detector DALI 230V



Version	Art. no.
	CCT556006

IR remote control for activating

- ARGUS presence detector DALI 230V - 2 zones master

Battery: CR2032

Range: up to 10 m

To be completed with: ARGUS Presence detector DALI 230V - 2 zones master CCT552006



The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.