


DR MOD 30 (953 011)

- High discharge capacity due to heavy-duty zinc oxide varistor / spark gap combination
- The plug-in protection module can be replaced without switching off the mains voltage and without removing the distribution board cover
- Easy replacement of protection modules without tools due to module locking system with module release button



Figure without obligation



Basic circuit diagram DR MOD 30



Dimension drawing DR MOD 30

Protection module with integrated Y protection circuit.

| Type | DR MOD 30 |
|-----------------------------------------------------------------|---------------|
| Part No. | 953 011 |
| Nominal discharge current (8/20 μ s) (I_n) | 1 kA |
| Total discharge current (8/20 μ s) [L+N-PE] (I_{total}) | 2 kA |
| Max. continuous operating voltage (a.c.) (U_c) | 30 V |
| Max. continuous operating voltage (d.c.) (U_c) | 30 V |
| Weight | 27 g |
| Customs tariff number (Comb. Nomenclature EU) | 85363030 |
| GTIN | 4013364109636 |
| PU | 1 pc(s) |

We reserve the right to introduce changes in performance, configuration and technology, dimensions, weights and materials in the course of technical progress. The figures are shown without obligation.