

KOVOVÉ SPÍNAČE IP 66

Koncový spínač s nerezovým čapom KSBM5E11-y

Zapojenie	Pracovný diagram	Typ
13-21, 14-22		KSBM5E11-Z11
13-21, 14-22		KSBM5E11-X11
13-21, 14-22		KSBM5E11-Y11
11-21, 12-22		KSBM5E11-W02
13-23, 14-24		KSBM5E11-W20
11-21, 12-22		KSBM5E11-Z02
13-21, 14-22, 31-32		KSBM5E11-X12
13-23, 14-24, 31-32		KSBM5E11-X21
11-21, 12-22, 31-32		KSBM5E11-W03
13-23, 14-24, 33-34		KSBM5E11-W30

Typ \ [mm]	A	B	C	ød	E	F ₁	F ₂
KSBM5E11-y	107	43	40	10	16	60	37

Koncový spínač s nerezovou kladkou KSBM5E13-y

13-21, 14-22		KSBM5E13-Z11
13-21, 14-22		KSBM5E13-X11
13-21, 14-22		KSBM5E13-Y11
11-21, 12-22		KSBM5E13-W02
13-23, 14-24		KSBM5E13-W20
11-21, 12-22		KSBM5E13-Z02
13-21, 14-22, 31-32		KSBM5E13-X12
13-23, 14-24, 31-32		KSBM5E13-X21
11-21, 12-22, 31-32		KSBM5E13-W03
13-23, 14-24, 33-34		KSBM5E13-W30

Typ \ [mm]	A	B	C	ød	E	F ₁	F ₂
KSBM5E13-y	120	43	40	12	16	60	50

Koncový spínač s nerezovým bočným čapom KSBM5E21-y

13-21, 14-22		KSBM5E21-Z11
13-21, 14-22		KSBM5E21-X11
13-21, 14-22		KSBM5E21-Y11
11-21, 12-22		KSBM5E21-W02
13-23, 14-24		KSBM5E21-W20
11-21, 12-22		KSBM5E21-Z02
13-21, 14-22, 31-32		KSBM5E21-X12
13-23, 14-24, 31-32		KSBM5E21-X21
11-21, 12-22, 31-32		KSBM5E21-W03
13-23, 14-24, 33-34		KSBM5E21-W30

Typ \ [mm]	A	B	C	ød	E	F ₁	F ₂
KSBM5E21-y	100,5	43	40	10	36	60	30,5